


Honda Radio Wire Harnesses


Up To 1986-1997/98



AS VIEWED FROM MATING END OF CONNECTOR

Pin	What It Is	Typical Honda/Acura In Dash Wire Color	"Typical" New Radio Equivalent Wire Color
A	Right Rear Spkr (+)	Red w/ Yellow Stripe	Purple
B	Left Rear Spkr (+)	Blue w/ Yellow Stripe	Green
C	Power Antenna Trigger	Brown w/ White Stripe	Blue or Blue w/ Wht Stripe
D	+12 Volt Ignition Wire	Yellow w/ Red Stripe	Red
E	Right Rear Spkr (-)	Brown w/ White Stripe	Purple w/ Black Stripe
F	Left Rear Spkr (-)	Gray w/ White Stripe	Green w/ Black Stripe
G	Ground Wire	Black	Black
H		Do Not Use	
I		Do Not Use	
J	+12 Volt Battery Wire	White w/ Yellow or Blu Stripe	Yellow
K	Dash Light Dimmer Wire		Orange
L	Left Front Spkr (+)	Blue w/ Green Stripe	White
M	Right Front Spkr (+)	Red w/ Green Stripe	Gray
N		Do Not Use	
O	Left Front Spkr (-)	Gray w/ Black Stripe	White w/ Black Stripe
P	Right Front Spkr (-)	Brown w/ Black Stripe	Gray w/ Black Stripe

1997-1998 And Newer



AS VIEWED FROM MATING END OF CONNECTOR

Pin	What It Is	Typical Honda/Acura In Dash Wire Color	"Typical" New Radio Equivalent Wire Color
A	Right Front Spkr (-)	Brown w/ Black Stripe	Gray w/ Black Stripe
B	Right Front Spkr (+)	Red w/ Green Stripe	Gray
C	Right Rear Spkr (-)	Brown w/ White Stripe	Purple w/ Black Stripe
D	Right Rear Spkr (+)	Red w/ Yellow Stripe	Purple
E		Do Not Use	
F		Do Not Use	
G		Do Not Use	
H	Dash Light Dimmer Wire		Orange
I	Honda Amp Ground Wire		
J	Left Front Spkr (-)	Gray w/ Black Stripe	White w/ Black Stripe
K	Left Front Spkr (+)	Blue w/ Green Stripe	White
L	Left Rear Spkr (-)	Gray w/ White Stripe	Green w/ Black Stripe
M	Left Rear Spkr (+)	Blue w/ Yellow Stripe	Green w/ Black Stripe
N	Ground Wire	Black	Black
O	+12 Volt Ignition Wire	Yellow w/ Red Stripe	Red
P	+12 Volt Battery Wire	White w/ Yellow Stripe	Yellow

Note: using an optional snap on wire harness adapter will simplify the wiring. Most snap on wire harness adapters have already converted and color coded the wires from the auto makers in dash wire harness to match typical aftermarket radio wire colors.

** The wire colors listed in the chart above are typical for these vehicles during these years but may not be the exact colors for this vehicle. This is another reason to use a snap on wire harness adapter. **

Honda - Isuzu Dual Use Radio Wire Harnesses

1996 And Newer



AS VIEWED FROM MATING END OF CONNECTOR

Pin	What It Is	Typical Isuzu-Honda In Dash Wire Color	Typical New Radio Equivalent Wire Color
A	Left Rear Spkr (+)	Orange	Green
B	Right Rear Spkr (+)	Orange w/ Blue Stripe	Purple
C	Left Rear Spkr (-)	White	Green w/ Black Stripe
D	Right Rear Spkr (-)	Orange w/ White Stripe	Purple w/ Black Stripe
E		Do Not Use	
F	+12 Volt Ignition Wire	Red w/ Yellow Stripe	Red
G	Ground Wire	Black	Black
H		Do Not Use	
I		Do Not Use	
J	Left Front Spkr (+)	Blue	White
K	+12 Volt Battery Wire	Red w/ White Stripe	Yellow
L	Left Front Spkr (-)	Yellow	White w/ Black Stripe
M	Right Front Spkr (+)	Green	Gray
N	Right Front Spkr (-)	Gray	Gray w/ Black Stripe

Note: using an optional snap on wire harness adapter will simplify the wiring. Most snap on wire harness adapters have already converted and color coded the wires from the auto makers in dash wire harness to match typical aftermarket radio wire colors.

** The wire colors listed in the chart above are typical for these vehicles during these years but may not be the exact colors for this vehicle. This is another reason to use a snap on wire harness adapter. **